

FD310H

Detector adicional Emisor/Receptor para la barrera FD310 configurable de 5 a 100m.

General

The FD310H consist of an infrared transmitter head and infrared receiver head, for expansion of the FD310. The FD310 ground level controller is supplied with one detector pair, and can support one additional FD310H.

The FD310 End to End infrared Optical Beam Smoke Detector (OBSD) has been designed using the latest optical technology, incorporating modern industrial, electronic and software techniques. This detector offers cost effective protection of large, open area spaces with high ceilings. It is also very suited to applications where access to ceiling mounted smoke detectors presents practical difficulties.

Operation

The system comprises a modern looking Transmitter head, which emits a narrow beam of infra-red light to an associated Receiver head, with a compact Low Level Controller. Once smoke crosses through and thus obscures the IR beam path, the signal strength at the Receiver drops below a preset level which in turn results in an alarm condition. Both the detector heads, Transmitter and Receiver, have integrated alignment thumbwheels for ease of alignment. Using these thumbwheels provides a smooth and repeatable alignment process. The detector heads have up to 10 degrees of adjustment in both planes. For further adjustment, a bespoke Adjustment Bracket is available, which offers up to 180 degrees movement in both planes, as well as a full 360-degree rotation.

The FD310 has been designed so that it can be installed by one operator, with its laser assisted alignment method combined with easy to use alignment LED's offering a visual feedback. Integrated laser alignment aid can be activated at the Controller or at the Receiver head.

The low level Controller incorporates a LCD display, which offers a full icon-based, easy-to-use interface unit. This Controller enables ease of commissioning, testing and maintenance of the beam detection system. During commissioning the detector sensitivity and fire thresholds can be selected, along with the user variable time to fire and time to fault settings.



Details

- Separate Transmitter and Receiver Heads
- Range 5 to 120 metres, configurable per set of Detectors
- Integral Laser Alignment in Receiver
- 2-wire Interface between Controller and Receiver
- Single and Twin Detector options
- Separate Fire and Fault Relays per Detector
- Low Level Controller with LCD display
- Programmable Sensitivity and Fire Threshold
- Automatic Gain Control (AGC) for drift compensation
- First Fix concept for Transmitter, Receiver and Controller
- Multiple cable gland knockouts for ease of wiring
- Optional Transmitter powering from Controller

FD310H

Detector adicional Emisor/Receptor para la barrera FD310 configurable de 5 a 100m.

Technical specifications

Electrical

Voltaje de funcionamiento	12 to 36 VDC
Consumo de corriente	14 mA (controller) 8 mA (transmission head)

Detection

Rango	5 to 120 m
-------	------------

Output

Ratio y tipo de salida	Relay output 2A @ 30 VDC
------------------------	--------------------------

Physical

Dimensiones físicas	74 x 74 x 161 mm (W x H x D)
Peso neto	104 g
Color	Blanco

Environmental

Temperatura de funcionamiento	-10 to +55°C
Entorno	Interior
Clasificación IP	IP54 (Controller and Heads)

Standards & regulations

Certificación	EN54-12
---------------	---------



Como empresa innovadora, Carrier Fire & Security se reserva el derecho de modificar las especificaciones de los productos sin previo aviso. Para conocer las últimas especificaciones de los productos, visite la Web de es.firesecurityproducts.com o póngase en contacto con su comercial.

Last updated on 25 May 2022 - 13:51